

Wireless Panda Keypad for LightSYS+

Model: RWX432KPP



The new 2-Way Panda wireless keypad for LightSYS+ is a programming keypad that provides full flexibility to place it where needed with no drilling and wiring. Its sleek design is perfect for users looking for a contemporary look and feel. With the ability to simulate Bus connection and function like the Wired Panda keypad, the wireless version connects seamlessly to the panel via the Wireless video module.

It receives real time status indications from the panel, cloud connectivity, and trouble and alarm notifications.

When combined with LightSYS+, the wireless keypad transforms your system into a fully wireless solution. Installation is a breeze, thanks to the incorporated mounting bracket and easy one-screw fixation.

In addition, the Panda wireless keypad has a flush mount accessory for smooth and discreet installation on the wall.

Experience the convenience and elegance of the new 2-Way Panda wireless keypad - the perfect choice for modern security systems.

Approvals



Europe



United Kingdom

EN50131

Europe

Features

- Durable and reliable and meet with the highest standards
- Intuitive user interface allows quick and easy control
- A comprehensive selection of keypads for any need

Technical specifications

Item	Product Specification
Current Consumption	Standby current 9µA, Max current 150 mA
Battery Type	CR123, 3V Lithium battery (x 4)
Typical Battery Life	3 years
Frequency	433.92 and 868.65 MHz
Proximity RF frequency	13.56 MHz
Dimensions (H x W x D)	178 x 103 x 38 mm (7.0 x 4.0 x 1.5")
Weight (Including batteries)	0.435 kg
Operating temperature	-10°C to 55°C (14°F to 131°F)
Storage temperature	-20°C to 70°C (-4°F to 158°F)

Ordering Information

Model	PN
WL Panda KP LightSYS+/Air&Prox 433MHz	RWX432KPP802A
WL Panda KP LightSYS+/Air&Prox 868MHz	RWX432KPP402A